



TDS Precision Products

TDS Precision Products GmbH
Industriestrasse 1a
CH-8157 Dielsdorf

T + 41 44 885 30 80
info@tds-pp.com
www.tds-pp.com



KVASER AIR BRIDGE LIGHT HS

EAN: 73-30130-00808-3 | (FCC) 73-30130-01008-6

Kvaser Air Bridge Light HS is a configuration-free wireless CAN bridge that achieves predictable latency, without sacrificing stability or range. Comprising a preconfigured pair of plug-and-play units to exchange raw CAN data, the Kvaser Air Bridge Light HS is designed for environments or situations that make wired connection unsuitable or challenging e.g., between two moving parts that are connected by CAN.

There are two versions: (00808-3) Kvaser Air Bridge Light HS is approved for the European Union, while (01008-6) Kvaser Air Bridge Light HS (FCC) complies with US certification. Both share the same functionality but have different radio transmission schemes due to regulatory differences.

Warranty

2-year warranty. See our General Conditions and Policies for details.

Support

Free support for all products by contacting support@kvaser.com.

Major Features

- IP65-rated aluminium housing, suitable for fixed outdoor installations.
- 2.4 GHz proprietary protocol. Internal antenna design, antenna output power max 18 dBm.
- Automatic baud rate detection (125K, 250K, 500K, 1M).
- Supports both 11-bit (CAN 2.0A) and 29-bit (CAN 2.0B active) identifiers.
- High-Speed CAN connection (compliant with ISO 11898-2), up to 1 Mbit/s. Plug and play, driver-free, and configuration-free.
- Power supplied through the CAN bus interface.
- Compatible with J1939, CANopen, NMEA 2000 and DeviceNet.
- Extended operating temperature range from -40 to +70 °C.

Software

Documentation, Kvaser CANlib SDK and drivers can be downloaded for free at www.kvaser.com/downloads.

Kvaser CANlib SDK is a free resource that includes everything you need to develop software for the Kvaser CAN interfaces. Includes full documentation and many program samples, written in C, C++, C#, Delphi, Visual Basic, Python and t programming language.

Kvaser CAN hardware is built around the same common software API. Applications developed using one device type will run without modification on other device types

Technical Data

Antenna Output Power	Max 18 dBm approx.
Antenna Type	Internal Antenna
CAN Bit Rate	Autobaud at 1 Mbit/s, 500 Kbit/s, 250 Kbit/s and 125 Kbit/s
CAN Channels	1
CAN Transceivers	TJA1051T
Casing Material	PC-ABS
Connector	DSUB 9 Male
Current Consumption	Approx. 2W
Dimensions	30 x 151 x 17 mm
Frequency Range	2.405 GHz to 2.477 GHz
IP Class	IP65
Operating Temperature Range	-40 °C to +70 °C
Packet Latency	Approx. 4.8ms
Weight	200g
Wireless Communication	2.4 GHz Gaussian Frequency-Shift Keying (GFSK) with Frequency Hopping Spread Spectrum (FHSS) modulation